



Flexibility at the core

- Two operating modes: Scenario Trigger and Fire Alarm
- In-app configuration of programmable actions
- Visual alarm verification using MotionCam detectors or any video camera connected to Ajax NVR
- Alarm delivery to CMS




Flawless hardware

- Simplified button mechanism reduces the risk of failure
- Up to 7 years of autonomous operation with pre-installed batteries
- Transparent protective lid prevents accidental alarm activation
- Tamper alarm



Smart and complex ecosystem

- Regular polling of the device to display current statuses in apps
- Automatic self-diagnosis with state reporting to the hub
- Up to 1,700 m of wireless communication and twice as much with a range extender
- Instant maintenance notifications



Quick installation and setup

- SmartBracket panel to mount the device: no need to disassemble the enclosure
- Lock to secure the device on SmartBracket
- Special tool (key) to reset the button after alarm
- Pairing with a hub via QR code
- Remote control and configuration in the app

Superior, Fibra, and Baseline product lines are mutually compatible. This opens up numerous possibilities for building systems of any configuration.

<p>Compatibility</p> <p>Hubs Hub Plus Jeweller Hub 2 (2G) Jeweller Hub 2 (4G) Jeweller Hub 2 Plus Jeweller Hub Hybrid (2G) Hub Hybrid (4G)</p> <p>Range extenders ReX ReX 2</p>	<p>Communication with hub</p> <p>Jeweller communication technology</p> <p>Frequency bands 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the sales region</p> <p>Communication range up to 1,700 m In an open space</p>	<p>Power supply</p> <p>Battery 2 × CR123A Pre-installed</p> <p>Battery life up to 7 years</p>	<p>Installation</p> <p>Operating temperature range from 0°C to +50°C</p> <p>Operating humidity up to 80%</p>
<p>Enclosure</p> <p>Dimensions 102 × 104 × 39 mm</p> <p>Weight 214 g</p> <p>Colour green, yellow, white, blue Depends on the selected version</p>	<p>Complete set</p> <p>ManualCallPoint Jeweller, SmartBracket mounting panel, 2 × CR123A battery (pre-installed), Special tool (key), Transparent protective lid, Installation kit, Quick start guide</p>		



For detailed information, scan the QR code or follow the link:

ajax.systems/support/devices/manualcallpoints-jeweller/



support@ajax.systems



@AjaxSystemsSupport_Bot



ajax.systems