

# HomeSiren

Wireless indoor siren that loudly notifies of an alarm during detector activation. It is installed indoors to warn of danger or deter intruders.

## Tech specs

Classification	Radio channel security sounder
Type of detector	Wireless
Installation method	Indoors
Compatibility	Operates only with <a href="#">Hub</a> , <a href="#">Hub Plus</a> and <a href="#">ReX</a>
Type of notification	Sound
Connector for external LED	Available
Sound volume level	Adjustable, 81–105 dB at a distance of 1 m
Alarm length	Adjustable, 3 s–15 min
Indication of armed/disarmed status	Yes
Alarm signal delivery time	0.15 s
Power supply	Battery: Two CR123A batteries Power supply voltage: 3 V Battery life – up to 5 years
Jeweller radio technology	Communication range with central unit – up to 2,000 m in an open space Two-way communication between devices Radio frequency bands: 866.0 – 866.5 MHz 868.0 – 868.6 MHz 868.7 – 869.2 MHz 905.0 – 926.5 MHz 915.85 – 926.5 MHz 921.0 – 922.0 MHz (depends on the region of sale)  Self-adjusting RF output power – up to 20 mW Block encryption based on AES algorithm Device polling period – 12–300 s  <a href="#">Learn more about Jeweller &gt;</a>
Temperature sensor	Available
Operating temperature range	-10°C to +40°C

Permissible humidity	Up to 75%
Protection class of body	IP50
Anti-sabotage	Protection against fraud Jamming detection Tamper-resistant
Remote setting and testing	+
Dimensions	75x76x27 mm
Weight	97 g
Certification	Grade 2, CE
Warranty	Replacement and repair within 24 months of the date of sale. Batteries are not covered under warranty.  <a href="#">Learn more &gt;</a>
Complete set	HomeSiren siren SmartBracket mounting panel Connector for LED indicator Two CR123A batteries (pre-installed) Installation set User's guide