

# Case C (260)

Casing for Ajax device and battery

<b>Compatibility</b>	LineSupply Fibra with a battery up to 7 Ah
<b>Device installation</b>	<p><b>Number of slots</b> 1 To install a different number of devices, select a model with the appropriate number of slots:</p> <ul style="list-style-type: none"><li>• Case A (106);</li><li>• Case B (175);</li><li>• Case D (430).</li></ul> <p><b>Plastic rails</b> to secure a module Slide LineSupply Fibra along the rails to remove it from the casing.</p> <p><b>Cable fasteners</b> to hold the cables together with ties</p> <p><b>Plastic stoppers</b> to protect the installed device During drilling, the instrument rests on the Case stoppers.</p> <p><b>Bubble level</b> To check the inclination angle of the casing during installation.</p> <p><b>Recesses for drilling</b> Ø20 mm or Ø32 mm The drill bit is fixed in the recess and does not move during drilling. We recommend using a hole saw for plastic.</p> <p><b>Wider holes</b> To ensure that the casing is installed correctly, even if there are errors during installation.</p> <p><b>Holders for a battery</b> up to 7 Ah To prevent accidental dislodgement of the battery.</p>

<p><b>Key features</b></p>	<p><b>Tamper board</b> Included in the Case complete set. The tamper board connects to the appropriate LineSupply Fibra connector and protects the installed device from sabotage.</p> <p><b>Holding screws</b> in the casing lid</p> <p><b>Latches</b> to secure the lid during installation The latches prevent the lid from falling off Case until it is secured with screws.</p>
<p><b>Recomendations</b></p>	<p>The device is designed for indoor use only. Case is produced in several versions.</p>
<p><b>Product</b></p>	<p><b>Dimensions</b> 260 × 195 × 93 mm 10.24" × 7.68" × 3.66"</p> <p><b>Weight of the black Case</b> 997 g 2.2 lb</p> <p><b>Weight of the white Case</b> 1,045 g 2.3 lb</p> <p><b>Operating temperature range</b> from -10 °C to +40 °C from 14 °F to 104 °F</p> <p><b>Operating humidity</b> up to 75%</p> <p><b>Protection class</b> IP20</p>
<p><b>Colours</b></p>	<p><b>Black</b> <b>White</b></p>
<p><b>Complete set</b></p>	<p>Case C (260) Tamper board Installation kit Quick start guide</p>
<p><b>Warranty</b></p>	<p>24 months</p>